

Switching DC Power Supply with USB Charger

Output 1-36 V, 0-3 A

Model 1550



The model 1550 is a compact 108 watt power supply delivering 1-36 V and 0-3 A from its main isolated output. A unique feature of the 1550 supply is the USB 1.1 charging port located on the front panel allowing the user to charge a cell phone or MP3 player. Clean power and quiet operation make this power supply ideal for any bench in laboratories, work shops and schools where bench space is limited.

Features:

- USB 1.1 charging port on front panel*
 - Rear panel security loop
 - Compact design
 - Output On/Off control
 - Large bright easy to read LCD display
 - Constant voltage and constant current operation
 - Overvoltage protection
- * USB 1.1 Charging port will not charge products compliant with USB 2.0 only

Specifications

	model
	1550

MAIN OUTPUT	
Output Voltage Adjustable Range	1.0 – 36 VDC
Output Current Adjustable Range	0 – 3 A
Voltage Regulation	
Load from 10 % to 100 %	±50 mV
Line from min to max	±20 mV
Ripple (rms)	±5 mV
Noise (Peak to Peak)	±50 mV
Current Regulation	
Load from 10 % to 100 %	±20 mA
Line from min to max	±20 mA
Switching Operation Frequency	80 kHz to 120 kHz
Efficiency at Max Power	83 % (±10 %)
Voltmeter and Ammeter Display	3 Digit
Voltmeter Accuracy	±1 % of rdg. ± 5 digits
Ammeter Accuracy	±1 % of rdg. ± 5 digits

USB OUTPUT	
Output Voltage	5 V (±10 %)
Output Current	400 mA (±10 %)
Load Voltage Regulation	80 mV (±10 %)
Ripple & Noise (no load rms)	8 mV (±10 %)

GENERAL	
Input Voltage	100 – 120 Vac (50~60 Hz) For 220V input version order model number 1550EXD
Full Load Input Current at 120 Vac	1.8 A (±10 %)
LCD Indication	CC, CV, Amp, Volt, Output ON-OFF
Protection	Short Circuit, Overload, Over Temperature, Over Voltage
Cooling System	Natural Convection
Dimensions (WxHxD)	2.8" x 6.0" x 9.8" (70 x 150 x 250 mm)
Weight	4.4 Lbs. (2 kgs)

One Year Warranty

Accessories
Supplied: User Manual, Power Cord

USB Charging Port

Charge your cell phone or MP3 player while you work

Rear Panel Security Loop

Secure the power supply to a work station to prevent unwanted removal