

400A DC/AC True RMS Watt Clamp Meter

Measure Watts, Current, and Voltage in hard to reach locations

Features:

- True RMS AC Voltage and Current
- DC and AC True Power to 240kW
- Highest resolution of any power clamp multimeter (10W or 100mA)
- 0.9" (23mm) jaw opening
- Large 4000 count LCD display
- Fast 40 segment analog bargraph current
- Auto Zero function for DC Current
- Data Hold, Max/Min recall display
- Frequency to 1MHz
- Low battery indication
- Complete with test leads, 2 AA batteries, and carrying case



CE  **CAT II-600V**

Specifications:	Range	Resolution	Accuracy \pm (%rdg+digits)	Input Signal Range
AC Power:	40kW	10W	\pm (1.5% + 3d)@50/60Hz	0-250V, 0-400A, PF 0-1
	240kW	100W	\pm (1.5% + 3d)@50/60Hz	0-600V, 0-400A, PF 0-1
DC Power:	40kW	10W	\pm (1.5% + 3d)	0-250V, 0-400A
	240kW	100W	\pm (1.5% + 3d)	0-600V, 0-400A
AC Current:	400A	100mA	\pm (1.5% + 3d)@50/60Hz	Overload protection: 600A AC (AC frequency range 40Hz-1kHz)
DC Current:	400A	100mA	\pm (1.5% + 3d)	Overload protection: 600A DC
AC Voltage:	600V	1V	\pm (1.5% + 2d)@50/60Hz	Overload protection: 800V AC
DC Voltage:	400V	0.1V	\pm (1.0% + 2d)	Overload protection: 800V DC
Frequency:	1MHz	0.01-100Hz	\pm (0.5% + 2d)	Overload protection: 600V AC
Dimensions:	7.2x2.5x1.4" (183x64x36mm)			
Weight:	6.7oz (190g including batteries)			

Ordering Information:

- 380940**400A AC/DC True RMS Watt Clamp-on
- 380940-NIST**.....400A AC/DC TRMS Watt Clamp-on with NIST Certificate
- 480172**AC Line Separator, 3-prong plug

