

VIDEO TV SIGNAL GENERATOR

The LG 226 TV Signal Generator modulates an analog TV signal in VSB for the PAL, NTSC and SECAM systems.

CE
Upon request

RoHS



LG 226 TV SIGNAL GENERATOR

GENERAL

The LG 226 TV Signal Generator provides the capability to modulate an analog TV signal in VSB-AM format applicable to the PAL, NTSC, and SECAM broadcasting systems.

The TV signals of VHF, UHF, and CATV channels can be generated by applying the external composite video signal and audio signal.

The full-field color bars and line sweep signals, and 1 kHz/400 Hz audio signals can also be generated.

This instrument can also be used as an analog TV signal modulator of the LT 450 Video Signal Generator since this instrument provides the LT 450 control capability.

FEATURES

- **Usage**
Suitable to check the video and sound of analog TV.
- **RF output frequency**
The RF frequency can be set from 30 MHz to 950 MHz in 50 kHz steps.
The channel table is provided to set the RF signal in channel instead of the frequency.

- **Output attenuator**
Highly reliable electronic attenuator is used.
- **Video modulation**
The VSB (Vestigial Sideband) modulation is used to eliminate the interference to of adjacent channels.
- **Sound modulation**
Applicable to both FM modulation and AM modulation (L method).
- **Preset function**
Up to 100 front panel settings can be stored and recalled.
- **Remote control function**
The preset conditions stored in the preset memory can be selected by specifying the address in INC, DEC, and RESET operation via the REMOTE control connector.
- **GPIB function**
All front panel keys except the POWER switch can be remotely controlled since the GPIB interface (conforming to IEEE488.1) is provided as standard.

LG 226 REAR PANEL



Test Equipment
Depot
1-800-517-8431

99 Washington Street
Melrose, MA 02176
Phone 781-665-1400
Toll Free 1-800-517-8431

Visit us at www.TestEquipmentDepot.com

SPECIFICATIONS

LG 226

RF Output

Frequency Range: 30 MHz to 950 MHz
Frequency Resolution: 50 kHz
Frequency Accuracy: 10 ppm
Frequency Switching Time: Within 100 ms
Frequency Setting
Channel Mode: Setting with a built-in channel table
Frequency Mode: Setting an arbitrary frequency
Output Impedance: 75 Ω
Output Connector: BNC
Output Level Range: -80 to 0 dBm (0 dBm max.)
Level Resolution: 1 dB
Output Level Accuracy: ±2 dB (0 to -9 dBm)
±3 dB (-10 to -80 dBm)
Spurious: Within -30 dBc (Harmonics)
Within -40 dBc (Non-Harmonics)

Video Signal

Modulation System: Amplitude modulation of the VSB (vestigial sideband) system according to a broadcast system
Modulation
At the time of built-in channel table setting:
87.5 %±3 % (Negative modulation)
97.0 %±3 % (Positive modulation)
At the time of arbitrary setting:
0 to 100 % (in 0.5 % steps)
Modulation Frequency Band
At the time of built-in channel table setting:
4.2 MHz/5.0 MHz/6.0 MHz (Depends on a broadcast system)
At the time of arbitrary setting:
4.2 MHz/5.0 MHz/6.0 MHz
Modulation Frequency Flatness: ±1 dB
Input Impedance: 75 Ω
Input Connector: BNC
Reference Input Level: 1 Vp-p
Spectrum Polarity: Positive (upper sound wave)
Built-in Pattern: Full-field Color Bar (NTSC/PAL)
Line sweep (at 100 % modulation: 4.2 MHz) (NTSC/PAL)

Sound Signal

Carrier Frequency
At the time of built-in channel table setting:
4.5 MHz/5.5 MHz/6.0 MHz/6.5 MHz (Depends on a broadcast system)
At the time of arbitrary setting:
4.5 to 6.5 MHz (in 0.5 MHz steps)
Video Sound Ratio
At the time of built-in channel table setting:
-6 dB/-7 dB/-10 dB (Depends on a broadcast system)
At the time of arbitrary setting:
-30 to 0 dB (in 1 dB steps)
Modulation Types: FM/AM (L System) (Depends on a broadcast system at the time of built-in channel table setting)
Frequency Deviation
At the time of a built-in channel table Setting:
15 kHz/30 kHz (equivalent to 60 % of the maximum deviation for each broadcasting system)
At the time of an arbitrary setting:
0 to 100 kHz (in 1 kHz steps)

Modulation (AM)

At the time of built-in channel table Setting:
60 %
At the time of arbitrary setting:
0 to 60 % (in 1 % steps)

Pre-Emphasis

At the time of built-in channel table setting:
75 μs/50 μs (Depends on a broadcast system)

At the time of arbitrary setting:
75 μs/50 μs/OFF

Modulation Frequency Response: 40 Hz to 100 kHz

Modulation Frequency Flatness: ±1 dB

Reference Input Level: 0 dBm (0.775 Vrms)

Input Impedance: 600 Ω

Input Connector: BNC

Built-in Sound Signal: Sine wave 400 Hz/1 kHz

* The modulation system cannot be selected at the time of channel mode.

Preset

Function: Up to 100 sets of panel settings can be stored and recalled.

GPIB

Function: Enables the key operations of the front panel except a power switch.
Connector: 24-pin rectangular connector 57LE-20240-7700D35G (DDK) or equivalent
Corresponding Standard: ANSI/IEEE Std 488.1-1987

REMOTE

Function: Enables the INC, DEC, and RESET operations of the preset memory.
Connector: 14-pin rectangular connector 57LE-4014-7700 (DDK) or equivalent
Input Level: TTL

RS232C

Function: Controls the Video signal generator LT 450, Selects the INC, DEC, or RESET/video format which are related to the PRESET-MEMORY.
Connector: 9-pin D-Sub (M)
Signal Format: Bidirectional serial data

Environmental Conditions

Operating Temperature: 0 to 40 °C
Operating Humidity: ≤85 %RH (without condensation)
Operating Environment: Indoor use
Operating Altitude: Up to 2,000 m
Overvoltage Category: II
Pollution Degree: 2

Power Requirements

Voltage: AC90 to 250 V
Power Frequency: 50/60 Hz
Power Consumption: 35 W max.

Dimensions

426(W) X 88(H) X 400(D) mm (excluding projections)

Weight

5.6 kg

Accessories

AC power cord..... 1
Instruction manual 1