



Visit us at www.TestEquipmentDepot.com

MODEL FC-2500

Frequency counter.

- Microprocessor counter measures to 2.5GHz
- High sensitivity in low/high ranges
- Max, Min & Average readings
- Relative frequency measurements
- Large 0.5" 8-digit LCD display
- Period display values from 10Hz to 10MHz
- Data Hold; Auto power off; Overload indication
- Gate time selector (Fast/Slow sampling time)



Range (Frequency):

Channel A: 50 MHz to 2500MHz,

Channel B: 10 MHz to 500 MHz,

Channel C: 10 Hz to 10MHz

Period: 10 Hz to 10 MHz

Maximum Resolution: 0.1 Hz

Sensitivity: Channel A, B, C: < 50 mV rms

Input Impedance: Channel A & B: 50 Ω typical,
Channel C: 1M Ω /30pF typical, AC coupled

FC-2500

Frequency Counter